

Installation Instructions

H-2003-0182

17-Aug-09

Software name - Details	File name	Ahead developing folder	Installation procedure	Installation procedure - details	Related driver etc.	Related driver etc. - details	Notice
Checknet	gprs_29_1_d030570.exe	c:\util2\drivers\gprs	Others	<ol style="list-style-type: none"> 1. Change "util2\drivers" to "util\drivers". 2. Run "setup.exe". 3. Press [Start Scan] at Winmux Driver Setup. (Write down COM of Information Port 1 at this moment) 4. When the scan is completed, press [Install Driver], [Close] and [Finish] in turn. 5. Reboot the computer. 6. When you open [Phone and Modem Option] from the control panel and are asked to input area code, input your area code and press [OK]. 7. press [Add...] at [Modems] tab. 8. Click on "Don't select my modem. I will select it from a list", and press [Next]. 9. Press [Hace Disk...], select "C:\program files\Panasonic\CheckNet\modem", and press [OK]. 10. Select "MC45(GPRS)" and press [Next] 11. Select "Com number" which you noted down before and press [Next]. 	no		
CheckNet Update	Checknet-2.11L10D-2kxp-nonlogo-M-web.zip or Checknet-2.11L11G-2kxp-nonlogo-M-web.zip			http://pc-dl.panasonic.co.jp/cgi-bin/itn/toughbook/dl02.cgi?main=4801			
CPU Idle Setting	cpupower_29_1_d030520.exe	c:\util2\cpupower	Executing "setup.exe"		no		
DMI viewer	dmi_29_1_d030557.exe	c:\util2\dmi	Executing "setup.exe"		no		
Hotkey Appendix	hkeyapp_29_1_d030450.exe	c:\util2\hkeyapp	Executing "setup.exe"		yes	Hotkey Driver, Hotkey Setting	
Hotkey Driver	hotkey_29_1_d030475.exe	c:\util2\drivers\hotkey	Executing [Update driver...] in the device manager	[Other devices]-[Unknown device]	yes	Hotkey Appendix, Hotkey Setting	
Hotkey Settings	hkeyset_29_1_d030477.exe	c:\util2\hkeyset	Executing "setup.exe"		yes	Hotkey Driver, Hotkey Appendix	
LAN Driver	lan_29_1_d010626.exe	c:\util2\drivers\lan	Executing [Update driver...] in the device manager	[Network adapters]-[Realtek RTL8139 Family PCI Fast Ethernet NIC]	no		
Modem driver	modem_29_1_d030388.exe	c:\util2\drivers\modem	Executing "setup.exe"		no		
OS INF file	intelif_29_1_d030128.exe	c:\intelif	Executing "setup.exe"		no		
Panasonic Hand Writing	writing_29_1_d030562.exe	c:\util2\writing	Executing "setup.exe"		no		
PC Information Viewer	pcinfo_29_1_d030561.exe	c:\util2\pcinfo	Executing "setup.exe"		no		
Resolution	resolution_29_1_d030495.exe	c:\util2\drivers\video	Others	Execute resolution.exe which is thawed.	no		
Simul Service	simulservice_29_1_d030494.exe	c:\util2\drivers\video	Others	Execute simulsvc.exe which is thawed.	no		
Sound Driver	sound_29_1_d030461.exe	c:\util2\drivers\sound	Executing [Update driver...] in the device manager	[Other devices]-[Multimedia Audio Controller]	no		
Touchpad/Touchscreen driver	mouse_29_1_d030178.exe	c:\util2\drivers\mouse	Executing [Update driver...] in the device manager	[Mice and other pointing devices]-[PS/2 Compatible Mouse]	no		
Video driver	video_29_1_d030395.exe	c:\util2\drivers\video	Others	<ol style="list-style-type: none"> 1. Run "C:\util2\drivers\video\Graphics\Setup.exe". (After the installation completed) 2. Run "C:\util2\drivers\video\IntelVGA.js". 3. Reboot the computer. 	no		

Wireless LAN Driver	wlan_29_1_d030423.exe	c:\util2\drivers\wlan	Others	<p>1. Install driver -> c:\util2\drivers\wlan\setupwld.exe 2. Install Intel Proset -> c:\util2\drivers\wlan\proset\proset.exe 3. Install Security Client -> c:\util2\drivers\wlan\leap\mtgh2kxp.msi</p> <p>* Only for German. 1. Complete Security at task tray. 2. Copy "%programme%\Intel\WLAN Security Client\mcd8021x.sys" to "%windows\system32\drivers". 3. Install "Installieren -Protocol - Meetinghouse Communications - IEEE 802.1x" in "Network properties - wirelessLAN Connection properties". 4. Reboot the computer.</p> <p>* Only for Spanish. 1. Complete Security Client at task tray. 2. Copy "%Archivos de programa%\intel\WLAN Security Client\mcd8021x.sys" to "%windows\system32\drivers". 3. Install "-Instalar... -Protocol - Meetinghouse Data Communications - IEEE 802.1x". 4. Reboot the computer.</p> <p>* Only for French. 1. Complete Security Client at task tray. 2. Copy "%Programmi%\intel\WLAN Security Client\mcd8021x.sys" to "%windows\system32\drivers". 3. Install "-Instalar... -Protocol - Meetinghouse Data Communications - IEEE 802.1x Protocol". 4. Reboot the computer.</p>	no		Only wireless LAN model can develop.
Wireless LAN Driver Update	wlan_d091074.exe wlan_d090756.exe			http://pc-dl.panasonic.co.jp/cgi-bin/itn/toughbook/dl02.cgi?main=16290			